

# Management Frames 00

- Association Request  
0000 ①
- Association Response  
0001 ②
- Reassociation Request  
0010 ③
- Reassociation Response  
0011 ④
- Probe Request  
0100 ⑤
- Probe Response  
0101 ⑥
- Reserved  
0110-0111
- Beacon  
1000 ⑦
- ATIM  
1001 (ad-hoc only)
- Disassociation  
1010 ⑧
- Authentication  
1011 ⑨
- Deauthentication  
1100 ⑩
- Reserved  
1101-1111

## Information Fields and Information Elements (with IE ID)\*

IE ID	Field Name	Type	Length	Size (Octets)
⑨	Authentication Algorithm Number	Fixed		2
⑨	Authentication Transaction Seq #	Fixed		2
⑥	Beacon Interval	Fixed		2
③	Current AP MAC Address	Fixed		6
①	Listen Interval	Fixed		2
⑧	Reason Code	Fixed		2
②	Association ID (AID)	Fixed		2
②	Status Code	Fixed		2
⑥	Timestamp	Fixed		8
①	SSID	Optional	0	2 - 34
①	Supported Rates	Optional	1	3 - 10
①	Ex Supported Rates	Optional	50	3 - 257
⑥	FH Parameter Set	Optional	2	7
⑥	DS Parameter Set	Optional	3	3
⑥	CF Parameter Set	Optional	4	8
⑥	IBSS Parameter Set	Optional	6	4
①	Capability Information	Fixed		2
⑦	Traffic Indication Map (TIM)	Optional	5	7 - 256
⑨	Challenge Text	Optional	16	3 - 255
⑥	ERP Information	Optional	42	3

## Size (Octets)

Auth Tran Sequence #	Auth Algorithm	Status Code	Challenge Text
1	Open System	Reserved	Not Present
2	Open System	Status	Not Present
1	Shared Key	Reserved	Not Present
2	Shared Key	Status	Present
3	Shared Key	Reserved	Present
4	Shared Key	Status	Not Present

## Reason Codes

- 0 - Reserved
- 1 - Unspecified Reason
- 2 - Previous authentication no longer valid
- 3 - Deauthenticated because sending station has left
- 4 - Disassociated due to inactivity
- 5 - Disassociation because the AP is overloaded
- 6 - Class 2 frame received from a non-authenticated STA
- 7 - Class 3 frame received from a non-authenticated STA
- 8 - Disassociated because sending station has left the BSS
- 9 - STA requesting (re)association is not authenticated with responding STA
- 10 - 65,535

## Status Codes

- 0 - Successful
- 1 - Unspecified Failure
- 2 - 9 Reserved
- 10 - Cannot support all requested capabilities
- 11 - Reassociation denied due to inability to confirm association
- 12 - Association denied due to reason outside the standard
- 13 - Responding STA doesn't support the specified auth algorithm
- 14 - Received an authentication frame with authentication transaction sequence number out of expected sequence
- 15 - Authentication rejected because of challenge failure
- 16 - Authentication rejected due to timeout waiting for next frame in sequence
- 17 - Association denied because the AP is unable to handle additional associated STA's
- 18 - Association denied due to requesting STA not supporting all of the data rates in the BSSBasicRateSetparameter
- 19 - Association denied due to requesting station not supporting Short Preamble
- 20 - Association denied due to requesting STA not supporting PBCC
- 21 - Association denied due to requesting STA not supporting Channel Agility
- 22 - 24 Reserved
- 25 - Association denied due to requesting STA not supporting Short Time Slot
- 26 - Association denied due to requesting STA not supporting DSSS-OFDM
- 27 - 65,535 Reserved

## Orig Standard

⑨	Authentication Algorithm Number	Fixed		.11
⑨	Authentication Transaction Seq #	Fixed		.11
⑥	Beacon Interval	Fixed		.11
⑤	Current AP Address	Fixed		.11
①	Listen Interval	Fixed		.11
⑧	Reason Code	Fixed		.11
②	Association ID (AID)	Fixed		.11
②	Status Code	Fixed		.11
⑥	Timestamp	Fixed		.11
①	SSID	Optional	0	.11
①	Supported Rates	Optional	1	.11
①	Ex Supported Rates	Optional	50	.11g
⑥	FH Parameter Set	Optional	2	.11
⑥	DS Parameter Set	Optional	3	.11
⑥	CF Parameter Set	Optional	4	.11
⑥	IBSS Parameter Set	Optional	6	.11
①	Capability Information	Fixed		.11
⑦	Traffic Indication Map (TIM)	Optional	5	.11
⑨	Challenge Text	Optional	16	.11
⑥	ERP Information	Optional	42	.11g

©Copyright 2005 - GTHill.com  
Comment / Questions - gene@gthill.com

## Station

CF Pollable	CF-Poll Request	Result
0	0	Not CF-Pollable
0	1	CF-Pollable - not desiring to be on CF Poll list
1	0	CF-Pollable - desiring to be on CF-Poll list
1	1	CF-Pollable - desiring never to be polled

## Access Point

CF Pollable	CF-Poll Request	Result
0	0	No Point Coordinator
0	1	Point coordinator for delivery only (does not poll)
1	0	Point coordinator for delivery and polling
1	1	Reserved



Capability Information Field Format

\* Fixed fields are required to be present in their respective frame types while others are optional depending on the circumstances